

5.8GHz 4W Signal Booster

Applications

IEEE 802.11a/n WLAN System
Smart Home Systems Signal Extender
Wireless Cameras Signal Extender
Drone Signal Extender



Features

80X the power, improving the link quality and coverage of certified WLAN devices
3.0dB ultra-low noise
Wide 6V to 16V operating input range
Working with certified IEEE 802.11a/n Wireless LAN devices
Simply plug and play, no software is required

Parameters

Number	Items	Specifications
1	Frequency Range	5725-5850MHz
2	Operating Voltage	6-16V
3	Receiving Gain	15dB ± 1
4	Transmission Gain:	19dB ± 1
5	Max Output Power(P1dB)	36dBm(4W)
6	Input Trigger Power	Min:3dBm Max:20dBm
7	EVM	3%@28dBm 802.11a 54Mbps OFDM 64QAM BW 20MHz
8	Noise Figure	<3.0dB
9	Current Supply	485mA@Pout 28dBm 12V
10	TX/RX Switch Time Delay	<1 us
11	LED Indicator	Transmitter: Green; Receiver: red
12	Operating Temperature	-30°C ~ +70°C
13	Storage Temperature	-40°C ~ +150°C
14	Operating Humidity	Up to 95% rel. humidity
15	RF Connector	Input: SMA-K; Output: RP-SMA-K
16	Power Socket	2.5*0.7mm DC(default) or 10cm red/black wire
17	Shell Size	76.6*35*14(mm)
18	Shell Material	Aluminum
19	Net Weight	0.06Kg

Attentions

- 1 12V /1A power supply.
 - 2 Heat dissipation is recommended, such as adding heat sink or radiator fan.
 - 3 Antenna should be screwed first, then plug the power adapter, finally connect the device.
 - 4 The output could reach 36dBm, when input power is 17dBm or 18dBm (default gain is 19dB).
-